

► PASIVOS DE DISTRIBUCION

«RMT» — Derivadores de Exterior 1000 MHz

CE

Derivadores 4 Salidas — Serie «RMT104»

Modelo RMT104-			-8	-11	-14	-17	-20	-23	-26
Referencia			2663	2664	2665	2666	2667	2668	2669
Atenuación de paso NOMINAL (MÁXIMA)	5 - 50 MHz	dB	T ⁽¹⁾	3,2 (3,7)	1,5 (1,9)	0,9 (1,4)	0,7 (1,1)	0,5 (0,9)	0,5 (0,9)
	50 - 600 MHz		T	4,1 (4,4)	2,0 (2,4)	1,2 (1,8)	0,8 (1,4)	0,7 (1,3)	0,6 (1,3)
	600 - 862 MHz		T	4,2 (4,6)	2,3 (3,0)	1,6 (2,4)	1,0 (1,8)	1,0 (1,6)	0,8 (1,6)
	862 - 1000 MHz		T	4,4 (4,9)	3,1 (3,7)	2,4 (3,1)	1,4 (2,2)	1,1 (1,8)	1,0 (1,8)
Atenuación de derivación	5 - 50 MHz	dB	7,0 ±1,0	10,3 ±1,0	13,7 ±1,0	17,7 ±1,0	20,2 ±1,0	23,1 ±1,0	25,5 ±1,0
	50 - 600 MHz		6,9 ±1,0	10,2 ±1,0	14,2 ±1,0	17,2 ±1,0	20,3 ±1,0	23,2 ±1,0	25,8 ±1,0
	600 - 862 MHz		7,2 ±1,7	10,4 ±1,7	14,3 ±1,7	16,4 ±1,7	20,1 ±1,7	22,7 ±1,7	25,7 ±1,7
	862 - 1000 MHz		7,4 ±2,0	10,8 ±2,0	14,2 ±2,0	15,7 ±2,0	20,6 ±2,0	23,5 ±2,0	26,3 ±2,0
Desacoplo direccional	5 - 50 MHz	dB	T ⁽¹⁾	≥18	≥20	≥26	≥35	≥35	≥38
	50 - 600 MHz		T	≥22	≥20	≥20	≥33	≥32	≥30
	600 - 862 MHz		T	≥20	≥19	≥19	≥30	≥28	≥26
	862 - 1000 MHz		T	≥18	≥18	≥18	≥28	≥27	≥25
Desacoplo entre salidas		dB	≥18						
Pérdidas de retorno		dB	≥15						
Paso de corriente en la línea principal			máx 6 A, 60 V (AC/DC)						
Modulación de zumbido (6A)		dB	≤ -70						
Dimensiones / Peso		mm/g	90 x 90 x 60 / 300						

⁽¹⁾ T → Terminal. El RMT104-8 es derivador de final de línea.