

► PASIVOS DE DISTRIBUCION

«RMT» — Derivadores de Exterior 1000 MHz

CE

Derivadores 8 Salidas — Serie «RMT108»

Modelo RMT108-			-11	-14	-17	-20	-23	-26
Referencia			2673	2674	2675	2676	2677	2678
Atenuación de paso NOMINAL (MÁXIMA)	5 - 50 MHz	dB	T ⁽¹⁾	3,3 (3,7)	1,5 (1,9)	1,0 (1,4)	0,8 (1,2)	0,7 (1,1)
	50 - 600 MHz		T	3,8 (4,4)	1,9 (2,5)	1,4 (1,9)	1,2 (1,7)	1,2 (1,3)
	600 - 862 MHz		T	4,0 (4,7)	2,2 (3,1)	1,5 (2,3)	1,2 (1,9)	1,0 (1,6)
	862 - 1000 MHz		T	4,2 (4,9)	2,5 (3,5)	2,1 (3,1)	1,3 (2,2)	1,1 (1,8)
Atenuación de derivación	5 - 50 MHz	dB	10,3 ±1,0	14,0 ±1,0	17,1 ±1,0	20,1 ±1,0	23,2 ±1,0	25,4 ±1,0
	50 - 600 MHz		10,3 ±1,0	13,7 ±1,0	17,6 ±1,0	20,3 ±1,0	23,5 ±1,0	25,9 ±1,0
	600 - 862 MHz		10,7 ±1,7	14,0 ±1,7	17,5 ±1,7	20,4 ±1,7	23,4 ±1,7	25,7 ±1,7
	862 - 1000 MHz		11,5 ±2,0	14,7 ±2,0	17,9 ±2,0	21,0 ±2,0	23,3 ±2,0	25,3 ±2,0
Desacoplo direccional	5 - 50 MHz	dB	T ⁽¹⁾	≥18	≥20	≥26	≥35	≥35
	50 - 600 MHz		T	≥22	≥20	≥20	≥33	≥32
	600 - 862 MHz		T	≥20	≥19	≥19	≥30	≥28
	862 - 1000 MHz		T	≥18	≥18	≥18	≥28	≥27
Desacoplo entre salidas		dB	≥18					
Pérdidas de retorno		dB	≥15					
Paso de corriente en la línea principal			máx 6 A, 60 V (AC/DC)					
Modulación de zumbido (6A)		dB	≤ -70					
Dimensiones / Peso		mm/g	130 x 95 x 55 / 500					

⁽¹⁾ T → Terminal. El RMT108-11 es derivador de final de línea.